

## Technical Information

# Vector+ Sensor Tap

---

<b>Dimensions</b>	150mm W x 133mm H x 47mm D, Spray nozzle height above basin surface 111mm, Spray nozzle projection from tap body 83mm
<b>Mounting requirements</b>	Any horizontal surface up to 40mm in thickness, requires a hole of 28-32mm in diameter
<b>Water supply</b>	0.5 to 6 bar operating pressure
<b>Sensor range</b>	Up to 18cm
<b>Run-on time</b>	2 seconds
<b>Power requirements</b>	6V DC from 4 x alkaline AA (LR6) batteries or 6V DC regulated from mains adaptor (1A fused spur required)
<b>Battery life</b>	2 years in normal conditions with recommended batteries (a single red flashing of the LED indicates that the batteries are low and need to be replaced)
<b>Electronic specification - power transformer</b>	100-250v AC 50/60Hz 0.2A MAX
<b>Electronic specification - Control Box Supply</b>	6V DC 1A MAX (batteries or power transformer)
<b>Ambient temperature range</b>	Operating: 0 to 40°C
<b>Storage</b>	-25 to 40°C

---